

## CONFIGURING UNITY FOR THE CISCO PAAS TWO PLATFORM

This document outlines the connectivity settings that must be set in the Kakapo portal when connecting to the Cisco PaaS platform. Please note all system providers will have their own DNS. All settings are configured in the Branding tab for the system provider in the Kakapo Partner Portal, in the Connectivity section, and come from the PaaS administration portal.

### OCI-P Interface

Unity uses the server address entered in Settings in the Unity client when connecting to the PaaS platform, so this should always be the same as the OCI-P OCS FQDN provided in the PaaS admin portal.

VoIP Server Port: 50034

Use OCI protocol over TLS:  OFF

OCI over TLS server port: 50034

OCI over TLS certificate host:

OCI over TLS security protocol: TLS 1.2

Type	URL	Protocol	Port
OCI-P OCS Interface	<b>vip.oci-us20.bclld.io</b>	TCP	50034

This is the VoIP server address to use in Unity Settings

This address must also be associated to the System Provider in the Kakapo portal, so ensure the user can be found when licensing. **The OCI-P FQDN must be associated with the system provider in the Kakapo portal before starting any Unity clients, otherwise the branding settings will not be downloaded, and Unity will not be able to connect to the PaaS platform. Please email [ineedhelp@kakaposystems.com](mailto:ineedhelp@kakaposystems.com) if assistance is required.**

Details Automatic Assignment Branding **Server Hostnames** Portal User Accounts License Details Resellers History Log User Templates

### Server Hostnames

Server hostnames currently used by this system provider.

Hostname
vip.oci-us20.bclld.io

Add Hostname

## CTI Interface

Use CTI instead of CAP protocol  ON

CTI Server Address

CTI Port

Use CTI protocol over TLS  OFF

CTI over TLS server port

CTI over TLS certificate host

CTI over TLS security protocol

## Computer Telephone Integration Interface

The Computer Telephony Integration interface provides TCP sockets that allow applications that you develop to integrate with Cloud PBX instances to perform telephony-related

### CTI IP Address Access Control List

You currently have no CTI ACL configured in this region 'North America'

[Add ACL](#)

### CTI Interfaces

Type	URL	Protocol	Port
CTI Interface	<a href="http://vip.cti-us20.bclid.io">vip.cti-us20.bclid.io</a>	TCP	50034

## XSI Interface

The URL of the XSI URL will include the Application IDs, which are com.broadsoft.xsi-actions and com.broadsoft.xsi-events. Only the URL should be set in the XSI Server Address field in the branding settings for the system provider, and because the Application IDs are the default values they do not need to be specified in the corresponding fields in the Kakapo portal; the Unity client will use the default Application IDs if they are not provided by the Kakapo portal.

XSI Server Address

XSI Server Security Type

XSI/CTI Actions Application ID

XSI/CTI Events Application ID

Reporting Server Address

Reporting Server Security Type

Reporting Server Application ID

### Extended Services Interface

The Extended Services Interface - Actions interface provides a set of RESTful APIs that allow access to Cloud PBX subscribers and services for BroadSoft Client Applications over HTTPS. The Extended Services Interface - Events interface provides a web application, which allows BroadSoft Client Applications to subscribe to Cloud PBX services for particular event packages via HTTPS.

Type	URL	Protocol	Port
XSI Actions Interface	<a href="https://vip.xsi-us20.bclid.io/com.broadsoft.xsi-actions">https://vip.xsi-us20.bclid.io/com.broadsoft.xsi-actions</a>	HTTPS	443
XSI Events Interface	<a href="https://vip.xsi-us20.bclid.io/com.broadsoft.xsi-events">https://vip.xsi-us20.bclid.io/com.broadsoft.xsi-events</a>	HTTPS	443

## Reporting Interface

This should be set to vip-c14811.openxsi-us20.bwks.io for all PaaS 2 system providers, however if Unity clients are unable to generate call center reports please raise a ticket with PaaS support to get the correct URL to use when connecting to the ECCR interface.